

# AVN-Portal Defaults Firmware

(AVN-PORTAL\_x.x.xxxx\_defaults.swu)

## Overview

This firmware resets your Sonifex unit to factory settings. If your unit enters "Recovery" mode due to a corrupted configuration, using this firmware will clear the existing configuration and restore the unit to its default settings. The unit will reboot automatically after installation, and you will need to reconfigure it.

## Warning

Using the "defaults" firmware will erase all custom configurations, including network settings and audio routes. After installation, you must manually reconfigure the unit and save a new configuration file.

## Recovery Webserver Address

To perform the recovery, connect your computer to the same network as the unit, and use the following address in your browser:

- **192.168.0.100:8080**

## Steps to Use

1. **Enter Recovery Mode:** Ensure the unit is in "Recovery" mode. If not, follow the standard recovery steps to access it.
2. **Access the Webserver:** In your browser, navigate to **http://192.168.0.100:8080**.
3. **Upload the Defaults Firmware:** On the recovery web interface, select and upload the "AVN-PORTAL\_x.x.xxxx\_defaults.swu" firmware file.
4. **Installation:** The unit will automatically install the firmware and reboot with default settings.
5. **Reconfigure the Unit:** After rebooting, manually reconfigure the unit and save a new configuration file.

## Notes

- The "defaults" firmware is for use only when other recovery methods have failed.
- Please save a new configuration file after reconfiguration to avoid future issues.

For assistance, contact Sonifex Technical Support.